


Multi Coin Acceptor

Step 1-Set up value



Code "H": Set up "15"
 Code "P": Output signal quantity: inset a coin usually, P1=01 for Lowest coin value, P+number=P1 multiply value rate
 Example: 2 dollar, 4 dollar: P1=01,P2=02
 Code "F": Set up "08"
Number: indicate rank of coin type

1. Hold on button "ADD" and "MINUS" simultaneously for seconds."A" shows up.
2. Hold on button "SET" for seconds."E" shows up.
 Use button "ADD" and "MINUS" to set up coin type.
 (First-Six Type is based on what mode you buy. EX: 923-> set up First-Third)
3. - Hold on button "SET" for seconds to switch to next code from H to F in cycle.
 - Please Use button "ADD" and MINUS to set up value.
 - Please hold on button "SET" for seconds to switch to next code
 - Please follow following table to set value for code.

First type		Second type		Third type		Forth type		Fifth type		Six type	
code	value	code	value	code	value	code	value	code	value	code	value
H1	15	H2	15	H3	15	H4	15	H5	15	H6	15
P1	SET	P2	SET	P3	SET	P4	SET	P5	SET	P6	SET
F1	08	F2	08	F3	08	F4	08	F5	08	F6	08
A	A shows up after F->Hold on button "SET" for seconds.										
E	E shows up after A->Power off and on when you see "E" AGAIN after A.										

Note:

- Usually, "F" is set up as 08, you can decrease value if you need more accuracy.
- If coin type is not up to 6, "E" shows after coin type reaches your setting.
 For example: If you set up coin type as 3, "E" shows up after F3. You can power off and on after finish "F3"
- If you want to change value few, free to hold on button "SET" to skip others.
- Setting example table: Page 2

Step 2-Sample Coin

1. Hold on button "SET" for seconds, and "A1" shows up from display.
2. Please insert coins of **TYPE 1** into coin entry until "A1" shows up again.
3. Please repeat **No.1** and **No.2** until all coin types are sampled.
4. Please power off and on.

Tip: If you want to re-sample few types, hold on button "SET" to skip others.

Multi Coin Acceptor

AP mode-Optional Function

AP mode: Collect multi pulse (P) to output 1 pulse (Range: 01-50)

EX: P=1 (pulse), Set up AP=03: Output 1 signal after collect 3 pulse

1. Please hold on button "SET" and "ADD" simultaneously for seconds, then hold on the button "SET" for seconds.
2. "AP" shows up. Please use button "ADD" and "MINUS" to adjust number.
3. Restart

Note: AP Mode Default is 01.

Reference video:

Step 1-Set up value: <https://youtu.be/1O6Y5vPQgjU> (00:00-00:40)

Step 2-Sample Coin: <https://youtu.be/1O6Y5vPQgjU> (00:41-2:30)

AP mode-Optional Function: https://youtu.be/-QV8Sv89_n4

More information: juyao66.com

Reference Setting Value

EURO										
First type		Second type		Third type		Forth type		Fifth type		See "A" after F5
code	value	code	value	code	value	code	value	code	value	
H1	15	H2	15	H3	15	H4	15	H5	15	
P1	<u>01</u>	P2	<u>02</u>	P3	<u>05</u>	P4	<u>10</u>	P5	<u>20</u>	
F1	08	F2	08	F3	08	F4	08	F5	08	
E	Please power off and on when you see "E" after A.									
Sample coins: A1: 10c,A2:20c, A3: 50c, A4: € 1, A5: € 2										
Power off after sample € 2										

USD										
First type		Second type		Third type		Forth type		Fifth type		See "A" after F5
code	value	code	value	code	value	code	value	code	value	
H1	15	H2	15	H3	15	H4	15	H5	15	
P1	<u>01</u>	P2	<u>02</u>	P3	<u>05</u>	P4	<u>10</u>	P5	<u>20</u>	
F1	08	F2	08	F3	08	F4	08	F5	08	
E	Please power off and on when you see "E" after A.									
Sample coins: A1: 10c,A2:20c, A3: 50c, A4:\$1, A5:\$2										
Power off after sample \$2										